

CHANGZHOU RILAND ELECTRONICS&MOTORS CO.,LTD
NO#121, CHANGHONG ROAD,WUJIN DISTRICT, JIANGSU PROVIENCE,CHINA

www.crl-motors.com

Email: jennifer@crl-motors.com Phone: +86 13961463772

Whatsapp: +86 13961463772

Wechat: shan19921226

Skype: 1377025329@qq.com

Fackbook: Jennifershan

Model	Poles	Voltage	Current	Resistance	Inductance	Max Static Torque	Weight
		V	A	Ω	mH	g.cm	KG
86BYGH001	4	4.4	2	22	7.7	22	1.7
86BYGH002	4	3	3	1	3.5	22	1.7
86BYGH003	4	2	4.5	0.5	1.5	22	1.7
86BYGH004	2	2.1	4.2	0.5	3.5	30	1.7
86BYGH101	4	6.4	2	3.2	14	44	2.8
86BYGH102	4	4.2	3	1.5	6	44	2.8
86BYGH103	4	2.8	4.5	0.66	2.5	44	2.8
86BYGH104	2	3	4.5	0.75	6	60	2.8
86BYGH201	2	7.6	2	3.8	19	66	3.8
86BYGH202	2	3.8	4	0.97	4.2	66	3.8
86BYGH203	2	2.5	6	0.42	1.7	66	3.8
86BYGH204	2	2.7	5.6	0.49	4.2	90	3.8

Sample customization and Demand customization.

Updated Date: 2018.07.17