

CHANGZHOU RILAND ELECTRONICS&MOTORS CO.,LTD
NO#121, CHANGHONG ROAD,WUJIN DISTRICT, JIANGSU PROVINCE,CHINA

www.crl-motors.com

Email: jennifer@crl-motors.com Phone: +86 13961463772

Whatsapp: +86 13961463772

Wechat: shan19921226

Skype: 1377025329@qq.com

Fackbook: Jennifershan

Model	Poles	Voltage	Current	Resistance	Inductance	Max Static Torque	Cogging Torque	Weight
		V	A	Ω	mH	g.cm	g.cm	KG
57BYGH001	4	7.4	1	7.4	10	1000	<250	0.7
57BYGH002	4	3.6	2	1.8	2.5	1000	<250	0.7
57BYGH003	4	2.3	3	0.75	1.1	1000	<250	0.7
57BYGH004	2	2.5	0.8	0.9	2.5	1000	<250	0.7
57BYGH201	4	8.6	1	8.6	14	1600	<300	1
57BYGH202	4	4.5	2	2.25	3.6	1600	<300	1
57BYGH203	4	3	3	1	1.6	1600	<300	1
57BYGH204	2	3.2	2.8	1.1	3.6	2000	<300	1
57BYGH205	2	1.4	4	0.35	2.4	2000	<300	1
57BYGH206	2	1.3	4.5	0.3	1.7	2000	<300	1
57BYGH301	2	1.6	4	0.4	2.6	2200	<300	1.2
57BYGH302	2	1.5	4.5	0.35	2	2200	<300	1.2
57BYGH401	2	1.8	4.5	0.4	2	2500		1.5

Sample customization and Demand customization.

Updated Date: 2018.07.17