

**CHANGZHOU RILAND ELECTRONICS&MOTORS CO.,LTD**  
**NO#121, CHANGHONG ROAD,WUJIN DISTRICT, JIANGSU PROVIENCE,CHINA**

[www.crl-motors.com](http://www.crl-motors.com)

Email: [jennifer@crl-motors.com](mailto:jennifer@crl-motors.com)

Phone: +86 13961463772

Whatsapp: +86 13961463772

Wechat: shan19921226

Skype: 1377025329@qq.com

Fackbook: Jennifershan

Model	Poles	Voltage	Current	Resistance	Inductance	Max Static Torque	Cogging Torque	Weight
		V	A	Ω	mH	g.cm	g.cm	KG
42BYG006	2	12	0.8	15	19	1600	<200	0.2
42BYG008	4	32	0.38	17	13,7	800	<150	0.2
42BYG008C	2	32	0.32	13.7	22.2	900	<150	0.2
42BYG009	2	22	0.6	7	6	1400	<180	0.2
42BYG012	2	24	0.52	9	11	1700	<220	0.2
42BYG014	4	8.4	0.45	19	13	1350	<200	0.2
42BYG015	4	12	0.3	40	19	1250	<200	0.2
42BYG016	4	24	0.32	75	55	1600	<200	0.2
42BYG017	2	27	0.42	15	16	1400	<180	0.2
42BYG020	4	12	0.6	20	14	1700	<200	0.2
42BYG023	2	12	0.4	30	36	2100	<220	0.2
42BYG025	2	24	0.8	21	2	1000	<200	0.2
42BYG026	4	9.6	0.4	24	13	1100	<200	0.2
42BYG205	4	9.6	0.48	20	15	1300	<220	0.24
42BYG228	4	12	0.4	30	23	2000	<220	0.24

*Sample customization and Demand customization.*

*Updated Date: 2018.07.17*